# LA8153QA

Monolithic Linear IC Down Converter IC for Digital CATV



## **Overview**

The LA8153QA is a down converter IC for digital CATV. It accepts RF input frequencies 50MHz to 150MHz. It has the power save function.

## **Functions**

- RF Mixer
- RF AGC amplifier
- Driver for SAW filter
- IF AGC amplifier
- IF Post amplifier for ADC
- Power save

## Application

- Digital Cable Set Top Boxes
- HDTV Receivers



VQFN28U

# **Specifications**

## **Maximum Ratings** at $Ta = 25^{\circ}C$

Parameter	Symbol	Conditions	Ratings	Unit
Maximum supply voltage	V <sub>CC</sub> max	Pins 3, 6, 17, 18, 27, 28	3.6	V
Circuit voltage	V max	Pin 11	V <sub>CC</sub>	V
Allowable power dissipation	Pd max	Ta $\leq$ 70°C, Mounted on a specified board. *	750	mW
Operating temperature	Topr		-20 to +70	°C
Storage temperature	Tstg		-55 to +150	°C

\* Specified board: 40mm × 50mm × 0.8mm, FR4, 4 layer, without soldering the Exposed Die Pad to PCB.

Stresses exceeding Maximum Ratings may damage the device. Maximum Ratings are stress ratings only. Functional operation above the Recommended Operating Conditions is not implied. Extended exposure to stresses above the Recommended Operating Conditions may affect device reliability.

#### **Recommended Operating Conditions** at Ta = 25°C

Parameter	Symbol	Conditions	Ratings	Unit
Recommended Supply Voltage	V <sub>CC</sub>	Pins 3, 6, 17, 18, 27, 28	3.3	V
Operating Supply Voltage Range	V <sub>CC</sub> op	Pins 3, 6, 17, 18, 27, 28	3.2 to 3.4	V

#### **ORDERING INFORMATION**

See detailed ordering and shipping information on page 7 of this data sheet.

# Electrical Characteristics at Ta = $25^{\circ}$ C, V<sub>CC</sub> = 3.3V

Deservator	Cumbal	Dia Na	Q = = = liti = = =		Ratings			
Parameter	Symbol Pin No.		Conditions	min	typ	max	Unit	
Circuit Current	Itotal	3, 6, 17, 18, 27, 28	No Signal	77	100	130	mA	
Power Save Current	lps	3, 6, 17, 18, 27, 28	No Signal	17	23	32	mA	
RF Input Frequency Range	f(RF)	8, 9	fc = -3dB	50		150	MHz	
RF AGC Range	GR1	27, 28	V11=2.5 to 0V	40	48		dB	
Mixer Conversion Gain	CG1	27 / 8 28 / 8	V11=2.5V	23	26	29	dB	
Mixer Inter Modulation 1	IM3 (1)	27 / 8 28 / 8	Input=70dBμV V11=2.5V	40	50		dB	
IF Input Frequency Range	f(IF)	23, 24	fc = -3dB	30		100	MHz	
IF Amplifier Gain	G(AGC)	19 / 23, 24 20 / 23, 24	V11=2.5V	50	54	58	dB	
IF Inter Modulation 2	IM3(2)	19 / 23, 24 20 / 23, 24	Output=105dBμV (99dBμV / tone)	50	60		dB	
IF AGC Range	GR2	19, 20	IF Output Level < ±1dB	3	5		dB	
IF AGC Output Level	V <sub>O</sub> (IF)1	19	Single output		0.5		Vp-р	
IF AGC Output Level	V <sub>O</sub> (IF)2	20	Single output		0.5		Vp-p	

# Package Dimensions

unit : mm

VQFN28 5x5, 0.5P / VQFN28U CASE 508AV ISSUE O



# Pin Assignment and Block Diagram



Pin Desc	cription at T	$a = 25^{\circ}C, V_{CC} = 3.3V$	
Pin No.	Pin voltage	Description	Equivalent circuit
1	-	NC (connect to GND)	
2	0.3V	PON	Vcc 2 1KΩ 2 - 1KΩ - 50kΩ - - - - - - - - - - - - -
3	3.3V	SAW Driver V <sub>CC</sub>	
4	0V	SAW Driver GND	
5	0V	RF AGC / MIX / LO GND	
6	3.3V	RF AGC / MIX / LO V <sub>CC</sub>	
7	_	NC (connect to GND)	
8 9	1.35V 1.35V	RF AGC Amplifier Input	
10	-	NC (connect to GND)	
11	_	AGC Control	
12, 13, 14	_	NC (connect to GND)	
15 16	1.6V 1.6V	LO Buffer Inputs	300Ω 300Ω 15 16 1mA 777 1mA 777
17	3.3V	IF AGC Amplifier V <sub>CC</sub>	
18	3.3V	Post Amplifier V <sub>CC</sub>	
19 20	1.0V 1.0V	Post Amplifier Outputs	VCC 19 300 20 Wh 7mA 7mA 7mA 7mA

Continued on next page.

Pin No.	Pin voltage	Description	Equivalent circuit
21	0V	Post Amplifier GND	
22	0V	IF AGC Amplifier GND	
23 24	2.5V 2.5V	IF AGC Amplifier Inputs	23 1 κΩ ₹ 1 κΩ 777 23 24 777 777 777 777 777 777 777
25, 26	_	NC (connect to GND)	
27 28	2.4V 2.4V	SAW Driver Outputs	27 28 5202 5202 5202 5202 5202 5202 5202 5

# AC Characteristics at Ta = $25^{\circ}$ C, V<sub>CC</sub> = 3.3V





# **Test Circuit**



## Attention

Electrostatic capacity of some pins is  $\pm 100$ V under the condition of C = 200pF and R = 0 $\Omega$ , so please handle carefully enough.

## **ORDERING INFORMATION**

Device	Package	Shipping (Qty / Packing)
LA8153QA-WH	VQFN28 5x5, 0.5P / VQFN28U (Pb-Free / Halogen Free)	2000 / Tape & Reel

ON Semiconductor and the ON logo are registered trademarks of Semiconductor Components Industries, LLC (SCILLC). SCILLC owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of SCILLC's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. SCILLC reserves the right to make changes without further notice to any products herein. SCILLC makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does SCILLC assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in SCILLC data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typical" must be validated for each customer application by customer's technical experts. SCILLC does not convey any license under its patent rights nor the rights of others. SCILLC products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the SCILLC product could create a situation where personal injury or death may occur. Should Buyer purchase or use SCILLC products for any such unintended or unauthorized use, even if such claim alleges that SCILLC was negligent regarding the design or manufacture of the part. SCILLC is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.