

CL1012 InGaP HBT Active Bias Gain Block 50MHz to 6000Mhz

RFMD SBB-5082S replacement^{*a,b*}

Criteria Labs CL1012 is a high-performance InGaP HBT MMIC amplifier utilizing a Darlington configuration with an active bias network in a hermetic package. The active bias network provides stable current over temperature and beta process variations. The CL1012 is designed for high linearity gain block military and industrial applications requiring excellent gain flatness, small size, minimal external components and hermetic packaging. Criteria Labs can provide various levels of device screening for military or high-reliability space applications.



Package: Hermetic, 2-pin, 5.8mm x 2.8mm

Product Features

- Single Fixed 5v Supply
- Hermetic Package for High Reliability Applications
- Ultra Flat Gain
- OIP3= 35dBm@ 1950MHz
- P1db=19dBm @ 1950MHz

Applications:

- Military and Space Communications
- Industrial Applications
- Aerospace and Defense



a. Suitability for model replacement within a system must be determined and is solely the responsibility of the customer.b. The RFMD SBB-5082S part number is used for identification and comparison purposes only.

C criteria labs

Criteria Labs 706 Brentwood St., Austin, TX 78752 www.criterialabs.com 512-637-4500

40-0012 Rev E

The information in this publication is believed to be accurate. However, no responsibility is assumed by Criteria Labs for its use, nor for any infringement of patents or other rights of third parties resulting from it use. No license is granted by implications or otherwise under any patent or patent rights of Criteria Labs. Criteria Labs reserves the right to change component circuitry, recommended application circuitry and specifications at any time without prior notice.

Page 1 of 5

Absolute Maximum Ratings		
Parameter	Rating	Units
Device Current (Id)	110	mA
Device Voltage	5.5V	V
RF Input Power	+24	dBm
Junction Temperature (Tj)	+150	°C
Operating Temperature Range	-40 to +85	°C
Storage Temperature Range	-65 to +150	°C
Moisture Sensitivity Level	Hermetic	
ESD Rating - Human body Model (HBM)	Class 1C	

Caution! ESD sensitive device.

Exceeding any one or a combination of the Absolute Maximum Rating conditions may cause permanent damage to the device. Extended application of Absolute Maximum Rating conditions to the device may reduce device reliability. Specified typical performance or functional operation of the device under Absolute Maximum Rating conditions is not implied.

Nominal Operating Parameters						
	Units	12 Specifications				Conditions
		Min	typ	Max	Units	
General Performance						Test conditions: Vd = 5Vdc, Id = 71mA, OIP3 tone spacing 1 MHz, Pout per tone = 5 dBm TL=25C, 50 ohm system. Bias Tee tested.
Small Signal Gain	dB	18	20	22	dB	1.95 GHz
	dB		17		dB	4 GHz
P1dB	dBm	17.5	18.2	20	dBm	1.95 GHz
OIP3	dB	31	35		dBm	1.95 GHz, 1.951 GHz
Input Return Loss	dB	13	18		dB	1.95 GHz
	dB		13		dB	4 GHz
Output Return Loss	dB	12	14		dB	1.95 GHz
	dB		8		dB	4 GHz
Reverse Isolation	dB	20	22.5		dB	1.95 GHz
Noise Figure	dB		3.7	4.4	dB	1.95 GHz
Operating Voltage	V		5		V	
Operating Current	mA	55	71	92	mA	
Thermal Resistance	C/W		87		°C/W	Junction to Case



Criteria Labs 706 Brentwood St., Austin, TX 78752 www.criterialabs.com 512-637-4500

40-0012 Rev E

The information in this publication is believed to be accurate. However, no responsibility is assumed by Criteria Labs for its use, nor for any infringement of patents or other rights of third parties resulting from it use. No license is granted by implications or otherwise under any patent or patent rights of Criteria Labs. Criteria Labs reserves the right to change component circuitry, recommended application circuitry and specifications at any time without prior notice.

Page 2 of 5

CL1012

20

18

16

14

12

4

2

0

5 4.5

4

3.5

8 2.5

2

1.5

1

0.5

0

1

1

2

-Cold

2

criteria labs

Typical Performance







CL1012

(P1dB v. Frequency)

- -Cold ---- Amb - - Hot

3 Frequency (GHz)

Amb - - Ho

3

Frequency (GHz)

4

5

CL1012 (NF v. Frequency) 4





Voltage (V)

Criteria Labs 706 Brentwood St., Austin, TX 78752 www.criterialabs.com 512-637-4500

80

70

60

50

30

20

10

0

₽ 40

40-0012 Rev E

The information in this publication is believed to be accurate. However, no responsibility is assumed by Criteria Labs for its use, nor for any infringement of patents or other rights of third parties resulting from it use. No license is granted by implications or otherwise under any patent or patent rights of Criteria Labs. Criteria Labs reserves the right to change component circuitry, recommended application circuitry and specifications at any time without prior notice.

6

-

5

6

Page 3 of 5

CL1012

Package Drawing



Pin Names and Descriptions		
Pin	Name	Description
1 RFIN	DEIN	RF input pin. This pin requires the use of an external blocking
		capacitor chosen for the frequency of operation
2	RFOUT/DC Bias	RF output and bias pin. This pin requires the use of an external
		blocking capacitor and inductor chosen for the frequency of operation.
Package Paddle	GND	Package backside must be connect to RF/DC ground



Criteria Labs 706 Brentwood St., Austin, TX 78752 www.criterialabs.com 512-637-4500

40-0012 Rev E

The information in this publication is believed to be accurate. However, no responsibility is assumed by Criteria Labs for its use, nor for any infringement of patents or other rights of third parties resulting from it use. No license is granted by implications or otherwise under any patent or patent rights of Criteria Labs. Criteria Labs reserves the right to change component circuitry, recommended application circuitry and specifications at any time without prior notice.

Page 4 of 5

CL1012

Typical Application Schematic







Criteria Labs 706 Brentwood St., Austin, TX 78752 www.criterialabs.com 512-637-4500

The information in this publication is believed to be accurate. However, no responsibility is assumed by Criteria Labs for its use, nor for any infringement of patents or other rights of third parties resulting from it use. No license is granted by implications or otherwise under any patent or patent rights of Criteria Labs. Criteria Labs reserves the right to change component circuitry, recommended application circuitry and specifications at any time without prior notice.

Page 5 of 5