

# Cascadable Amplifier 100 to 2000 MHz

Rev. V4

#### **Features**

• LOW NOISE FIGURE: 3.5 dB (TYP.)

• HIGH THIRD ORDER IP: +32 dBm (TYP.)

• HIGH OUTPUT LEVEL: +21 dBm (TYP.)

• LOW VSWR: 1.8:1 (TYP.)

#### **Description**

The A32 RF amplifier is a discrete hybrid design, which uses thin film manufacturing processes for accurate performance and high reliability.


This single stage GaAs FET feedback amplifier design displays impressive performance characteristics over a broadband frequency range. An RF choke is used for DC power supply decoupling.

Both TO-8 and Surface Mount packages are hermetically sealed, and MIL-STD-883 environmental screening is available.

#### **Ordering Information**

Part Number	Package
A32	TO-8
SMA32	Surface Mount
CA32	SMA Connectorized

#### **Product Image**



# Electrical Specifications: $Z_0 = 50\Omega$ , $V_{CC} = +15 V_{DC}$

Parameter	Units	Typical	Guaranteed	
Parameter		25°C	0° to 50°C	-54° to +85°C*
Frequency	MHz	10-2000	10-2000	10-2000
Small Signal Gain (min)	dB	10.0	9.0	8.5
Gain Flatness (max)	dB	±3.0	±0.7	±1.0
Reverse Isolation	dB	20		
Noise Figure (max)	dB	3.5	4.0	4.5
Power Output @ 1 dB comp. (min)	dBm	21.0	19.0	18.0
IP3	dBm	+32		
IP2	dBm	+38		
Second Order Harmonic IP	dBm	+40		
VSWR Input / Output (max)		1.8:1 / 1.8:1	2.1:1 / 2.1:1	2.3:1 / 2.3:1
DC Current @ 15 Volts (max)	mA	94	98	100

# **Absolute Maximum Ratings**

Parameter	Absolute Maximum	
Storage Temperature	-62°C to +125°C	
Case Temperature	+125°C	
DC Voltage	+17 V	
Continuous Input Power	13 dBm	
Short Term Input power (1 minute max.)	50 mW	
Peak Power (3 µsec max.)	0.5 W	
"S" Series Burn-In Temperature (case)	+125°C	

#### Thermal Data: $V_{CC} = +15 V_{DC}$

Parameter	Rating
Thermal Resistance $\theta_{jc}$	182°C/W
Transistor Power Dissipation P <sub>d</sub>	0.288 W
Junction Temperature Rise Above Case T <sub>jc</sub>	+52°C

<sup>1 \*</sup> Over temperature performance limits for part number CA32, guaranteed from 0°C to +50°C only.




Cascadable Amplifier 100 to 2000 MHz

Rev. V4


#### Typical Performance Curves at +25°C

### Gain 10.0 W 10.0 9.8 50 100 400 700 1000 1300 1600 FREQUENCY - MHz Noise Figure FIGURE - dB 5.0 100 700 1000 1300 FREQUENCY - MHz Power Output\* POWER 0.01PUT - 48 700 1000 1300 10 50 100 1600 1900 2200 400 FREQUENCY - MHz \* at 1 dB Gain Compression Intercept Point 2ND HARMONIC INTERCEPT POINT FOINT - dBm POINT - dBm 3RD ORDER INTERCEPT POINT 400 700 1000 1300 1600 1900 2200 100 **EREQUENCY - MHz VSWR** 400 700 1000 1300 1600 1900 2200 FREQUENCY - MHz


# Outline Drawing: TO-8 \*



## Outline Drawing: Surface Mount



# Outline Drawing: SMA Connectorized \*



\* Dimensions are inches (millimeters) ±0.015 (0.38) unless otherwise specified.

# A32 / SMA32



Cascadable Amplifier 100 to 2000 MHz

Rev. V4

#### M/A-COM Technology Solutions Inc. All rights reserved.

Information in this document is provided in connection with M/A-COM Technology Solutions Inc ("MACOM") products. These materials are provided by MACOM as a service to its customers and may be used for informational purposes only. Except as provided in MACOM's Terms and Conditions of Sale for such products or in any separate agreement related to this document, MACOM assumes no liability whatsoever. MACOM assumes no responsibility for errors or omissions in these materials. MACOM may make changes to specifications and product descriptions at any time, without notice. MACOM makes no commitment to update the information and shall have no responsibility whatsoever for conflicts or incompatibilities arising from future changes to its specifications and product descriptions. No license, express or implied, by estoppels or otherwise, to any intellectual property rights is granted by this document.

THESE MATERIALS ARE PROVIDED "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, RELATING TO SALE AND/OR USE OF MACOM PRODUCTS INCLUDING LIABILITY OR WARRANTIES RELATING TO FITNESS FOR A PARTICULAR PURPOSE, CONSEQUENTIAL OR INCIDENTAL DAMAGES, MERCHANTABILITY, OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT. MACOM FURTHER DOES NOT WARRANT THE ACCURACY OR COMPLETENESS OF THE INFORMATION, TEXT, GRAPHICS OR OTHER ITEMS CONTAINED WITHIN THESE MATERIALS. MACOM SHALL NOT BE LIABLE FOR ANY SPECIAL, INDIRECT, INCIDENTAL, OR CONSEQUENTIAL DAMAGES, INCLUDING WITHOUT LIMITATION, LOST REVENUES OR LOST PROFITS, WHICH MAY RESULT FROM THE USE OF THESE MATERIALS.

MACOM products are not intended for use in medical, lifesaving or life sustaining applications. MACOM customers using or selling MACOM products for use in such applications do so at their own risk and agree to fully indemnify MACOM for any damages resulting from such improper use or sale.