# MACS-007802-0M1RS0

# Stereo Doppler Transceiver 24.125 GHz

#### Features

- Low Cost
- Compact Size
- Gold Plated Solder Pins
- Detects Direction of Motion
- Rugged Die cast Construction
- 10Hz 5000Hz IF Bandwidth
- Lead Free (RoHS\* Compliant)

Product Specifications

### **Description and Applications**

M/A-COM's MACS-007802-0M1RS0 is a RoHS Compliant K-Band Stereo Doppler transceiver consisting of a Gunn Diode oscillator and two Schottky Diode mixers assembled into a die cast waveguide package.

These Transceivers are well suited for high volume applications where small size and reliability are required. Typical applications include automatic door openers, police radar and presence sensing applications, where Direction of motion is required.

| Parameter                  | Test<br>Conditions | Units           | Min.   | Тур.   | Max.   |
|----------------------------|--------------------|-----------------|--------|--------|--------|
| Operating<br>Frequency     | +25 ⁰C             | GHz             | 24.100 | 24.125 | 24.150 |
| Output Power               | +25 ⁰C             | mW              | 5.0    |        |        |
| Operating<br>Current       | +25 °C             | mA              | 60     | 85     | 100    |
| Operating<br>Voltage       | +25 °C             | VDC             |        | 5.0    |        |
| Schottky Diode<br>Noise    | +25 °C             | micro-<br>Volts |        | 2.5    | 5.0    |
| Transceiver<br>Sensitivity | +25 ⁰C             | -dBc            | -93    | -103   |        |
| Mixer Phasing              | +25 ⁰C             | Degrees         | 50     |        | 120    |

Operating temperature to full specification -30°C to +70°C

### Absolute Maximum Ratings<sup>1</sup>

1

| Parameter               | Maximum Ratings   |  |  |
|-------------------------|-------------------|--|--|
| Operating Temperature   | -40 °C to +85 °C  |  |  |
| Storage Temperature     | -65 °C to +150 °C |  |  |
| Incident RF Input Power | +20 dBm           |  |  |
| DC Input (Gunn Diode)   | +5.5VDC           |  |  |
| Soldering Temperature   | +260 °C max.      |  |  |

1. Exceeding these limits may cause permanent damage.

# Note: Device is ESD Sensitive. Proper ESD Precautions should be used when handling this Device..

#### **Package Outline**



#### **PIN Configuration**

| PIN | Function            |  |  |
|-----|---------------------|--|--|
| 1   | DC Input            |  |  |
| 2   | GND                 |  |  |
| 3   | IF Output (Mixer 1) |  |  |
| 4   | IF Output (Mixer 2) |  |  |

### **Functional Block Diagram**



\*Restrictions on Hazardous Substances, European Union Directive 2002/95/EC.

• North America Tel: 800.366.2266 • Europe Tel: +353.21.244.6400

- India Tel: +91.80.43537383 China Tel: +86.21.2407.1588
- Visit www.macomtech.com for additional data sheets and product information.

**PRELIMINARY**: Data Sheets contain information regarding a product M/A-COM Technology Solutions has under development. Performance is based on engineering tests. Specifications are typical. Mechanical outline has been fixed. Engineering samples and/or test data may be available. Commitment to produce in volume is not guaranteed.

ADVANCED: Data Sheets contain information regarding a product M/A-COM Technology Solutions

is considering for development. Performance is based on target specifications, simulated results, and/or prototype measurements. Commitment to develop is not guaranteed.

> M/A-COM Technology Solutions Inc. and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice.



Rev. V4

# MACS-007802-0M1RS0



## Stereo Doppler Transceiver 24.125 GHz

Rev. V4



- **ADVANCED:** Data Sheets contain information regarding a product M/A-COM Technology Solutions is considering for development. Performance is based on target specifications, simulated results, and/or prototype measurements. Commitment to develop is not guaranteed.
  - North America Tel: 800.366.2266 Europe Tel: +353.21.244.6400 • India Tel: +91.80.43537383 • China Tel: +86.21.2407.1588
  - Visit www.macomtech.com for additional data sheets and product information.

changes to the product(s) or information contained herein without notice.